

42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Features

- Qualified for Automotive Applications:
 - AEC-Q100 Grade 1, T_A : -40°C to $+125^{\circ}\text{C}$
 - Junction Temperature, T_J : -40°C to $+150^{\circ}\text{C}$
- Input Voltage: 3 V to 42 V
- Output Voltage:
 - Adjustable from 0.6 V to 21 V
- $\pm 2\%$ Output Accuracy Over Line Regulation, Load Regulation, and Operating Temperature Range
- Low Current Consumption:
 - 1- μA Shutdown Current
 - 5- μA Typical Quiescent Current
- 450-mA Maximum Output Current
- Low Dropout Voltage: 700 mV typical at 400-mA Load Current
- Stable with 1- μF to 200- μF Output Capacitor with ESR Range from 0.001 Ω to 5 Ω
- Integrated Protection:
 - Over-Current Protection
 - Over-Temperature Protection
- Package Option:
 - EMSOP8

Applications

- Automotive Clusters and Infotainment
- Automotive Headlights and Interior Lighting
- Automotive Domain Control
- Automotive BCM and Door Handler

Description

The TPL8052Q series supports operating with 3 V to 42 V (45-V maximum transient voltage). Operating with as low as 3 V allows the TPL8052Q to continue to work well during cold-crank and start-stop conditions.

The TPL8052Q is a series of 5- μA ultra-low quiescent low dropout voltage linear regulators with 450-mA maximum output current capability.

With the above features, the TPL8052Q products are the optimal solutions for powering the MCU, CAN/LIN transceivers in the always-on applications, and the battery-connected applications in the automotive systems.

The TPL8052Q series provides adjustable output voltage options, and the TPL8052Q supports a wide range of output capacitors from 1 μF to 200 μF with an ESR range from 0.001 Ω to 5 Ω . Also, the TPL8052Q series integrates over-current protection and over-temperature protection.

The TPL8052Q series operates in the ambient temperature range from -40°C to $+125^{\circ}\text{C}$.

Typical Application Circuit




Table of Contents

Features	1
Applications	1
Description	1
Typical Application Circuit	1
Product Family Table	3
Revision History	3
Pin Configuration and Functions	4
Specifications	5
Absolute Maximum Ratings	5
ESD, Electrostatic Discharge Protection.....	5
Recommended Operating Conditions.....	5
Thermal Information.....	5
Electrical Characteristics.....	6
Typical Performance Characteristics.....	8
Detailed Description	10
Overview.....	10
Functional Block Diagram.....	10
Feature Description.....	10
Application and Implementation	12
Application Information	12
Typical Application.....	12
Layout	13
Layout Guideline.....	13
Tape and Reel Information	14
Package Outline Dimensions	15
EMSOP8.....	15
Order Information	16
IMPORTANT NOTICE AND DISCLAIMER	17

**42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout
Linear Regulator****Product Family Table**

Order Number	Output Voltage (V)	Package
TPL8052ADQ-EV1R-S	Adjustable (0.6 V to 21 V)	EMSOP8

Revision History

Revision	Notes
Rev.P.0	Preliminary Datasheet.
Rev.A.0	Initial release

42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Pin Configuration and Functions




Table 1. Pin Functions: TPL8052Q

Pin Number	Pin Name	I/O	Description
2	EN	I	Regulator enable pin. Drive EN high to turn on the regulator and drive EN low to turn off the regulator.
7	FB	I	Output feedback pin. Connect a resistor divider from OUT to FB and FB to GND to set the output voltage.
4	GND	-	Ground reference pin. Connect GND pin to PCB ground plane directly.
1	IN	I	Input voltage pin.
3, 5, 6	NC	-	No connection.
8	OUT	O	Regulated output voltage pin.

(1) Thermal Pad **MUST** be connected to PCB ground plane directly.

42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Specifications

Absolute Maximum Ratings

Parameter		Min	Max	Unit
EN, IN		-0.3	45	V
OUT		-0.3	45	V
FB		-0.3	20	V
T _J	Junction Temperature Range	-40	150	°C
T _{STG}	Storage Temperature Range	-65	150	°C
T _L	Lead Temperature (Soldering 10 sec)		260	°C

- (1) Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. Exposure to any Absolute Maximum Rating condition for extended periods may affect device reliability and lifetime.
- (2) All voltage values are with respect to GND.
- (3) Not subject to production test, specified by design.

ESD, Electrostatic Discharge Protection

Symbol	Parameter	Condition	Minimum Level	Unit
HBM	Human Body Model ESD	AEC Q100-002	±2	kV
CDM	Charged Device Model ESD	AEC Q100-011	±1	kV

Recommended Operating Conditions

Parameter		Min	Max	Unit
IN		3	42	V
EN		0	V _{IN}	V
OUT		0	21	V
C _{OUT} ⁽¹⁾⁽²⁾	Output Capacitor Requirements	1	200	μF
ESR ⁽²⁾	Output Capacitor ESR Requirements	0.001	5	Ω
T _A	Ambient Temperature Range	-40	125	°C

- (1) The minimum output capacitance requirement is applicable for a worst-case capacitance tolerance of 30%.
- (2) Not subject to production test, specified by design.

Thermal Information

Package Type	θ _{JA}	θ _{JB}	θ _{JC, TOP}	Unit
EMSOP8	45.6	43.3	95.2	°C/W

42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Electrical Characteristics

All test conditions: $V_{IN} = 13.5\text{ V}$, $V_{EN} = 2\text{ V}$, $C_{IN} = C_{OUT} = 10\text{ }\mu\text{F}$, $I_{OUT} = 0.1\text{ mA}$. $T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$, unless otherwise noted.

Symbol	Parameter	Conditions	Min	Typ	Max	Unit
Supply Input Voltage and Current						
V_{IN}	Input Supply Voltage Range ⁽¹⁾		$V_{IN, MIN}$		42	V
UVLO	V_{IN} Under-Voltage Lockout Threshold	V_{IN} rising, $V_{EN} = 2\text{ V}$, $I_{OUT} = 0.1\text{ mA}$		2.7	2.9	V
	Hysteresis			270		mV
I_{SD}	Shutdown Current	$V_{EN} = 0\text{ V}$, $V_{IN} = 13.5\text{ V}$		1	3	μA
I_Q	Quiescent Current	$I_{OUT} = 0\text{ mA}$, $V_{IN} = 13.5\text{ V}$		5	10	μA
		$I_{OUT} = 0.1\text{ mA}$, $V_{IN} = 13.5\text{ V}$		6	12	μA
		$I_{OUT} = 100\text{ mA}$, $V_{IN} = 13.5\text{ V}$		400		μA
Enable Input Voltage and Current						
$V_{IH, EN}$	EN Logic Input High (Enable)		2		V_{IN}	V
$V_{IL, EN}$	EN Logic Input Low (Disable)		0		0.7	V
I_{EN}	EN Pin Leakage Current	$V_{EN} = 2\text{ V}$ to 42 V		100		nA
Regulated Output Voltage and Current						
V_{FB}	Feedback Voltage	$V_{IN} = 6.5\text{ V}$ to 42 V , $V_{OUT} = V_{FB}$	0.588	0.6	0.612	V
I_{FB}	FB Pin Leakage Current	$V_{IN} = 6.5\text{ V}$ to 42 V , $V_{FB} = 1.3\text{ V}$		100		nA
V_{OUT}	Output Accuracy	$V_{IN} = 6.5\text{ V}$ to 42 V , $I_{OUT} = 1\text{ mA}$ to 450 mA	-2%		2%	
ΔV_{OUT}	Line Regulation	$V_{IN} = 6.5\text{ V}$ to 42 V , $I_{OUT} = 1\text{ mA}$		0.004		%/V
	Load Regulation	$V_{IN} = 6.5\text{ V}$, $I_{OUT} = 1\text{ mA}$ to 450 mA		0.0005		%/mA
V_{DO}	Dropout Voltage ⁽²⁾	$I_{OUT} = 200\text{ mA}$, $V_{OUT} = 3.3\text{ V}$		375	600	mV
		$I_{OUT} = 400\text{ mA}$, $V_{OUT} = 3.3\text{ V}$		750	1200	mV
		$I_{OUT} = 200\text{ mA}$, $V_{OUT} = 5\text{ V}$		350	600	mV
		$I_{OUT} = 400\text{ mA}$, $V_{OUT} = 5\text{ V}$		700	1000	mV
I_{OUT}	Output Current Range	V_{OUT} in regulation	0		450	mA
I_{CL}	Output Current Limit	V_{OUT} is forced to $0.9 \cdot V_{OUT(NOM)}$	451	600	700	mA
t_{SU}	Start-Up Time ⁽³⁾	From $EN \geq V_{IH}$, EN to $OUT \geq 95\%$ of $V_{OUT(NOM)}$		4		ms
PSRR	Power Supply Rejection Ratio ⁽³⁾	$I_{OUT} = 10\text{ mA}$, $f = 1\text{ kHz}$		50		dB
		$I_{OUT} = 10\text{ mA}$, $f = 100\text{ kHz}$		45		dB
Temperature Range						
T_{SD}	Thermal Shutdown Threshold ⁽³⁾			175		$^\circ\text{C}$
	Thermal Shutdown Hysteresis ⁽³⁾			20		$^\circ\text{C}$

(1) $V_{IN, MIN} = 3\text{ V}$ or $V_{OUT(NOM)} + 1\text{ V}$, whichever is greater.


**42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout
Linear Regulator**

- (2) Dropout voltage is the minimum input-to-output voltage differential needed to maintain regulation at a specified output current. Dropout voltage is measured when the output voltage has dropped 100 mV from the nominal value. In dropout, the output voltage will be equal to $(V_{IN} - V_{DO})$.
- (3) Not test during production.


42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Typical Performance Characteristics

All test conditions: $V_{IN} = 13.5\text{ V}$, $V_{EN} = 2\text{ V}$, $C_{IN} = C_{OUT} = 10\text{ }\mu\text{F}$, $I_{OUT} = 0.1\text{ mA}$. $T_A = -40^\circ\text{C}$ to $+125^\circ\text{C}$, unless otherwise noted.




42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator




$C_{OUT} = 10 \mu F$, $V_{IN} = 6 V$ to $42 V$

Figure 7. Line Transient



$C_{OUT} = 10 \mu F$, $I_{OUT} = 10 mA$ to $450 mA$

Figure 8. Load Transient



$C_{OUT} = 10 \mu F$, $V_{OUT} = 0 V$ to $5 V$

Figure 9. Startup Waveform

Detailed Description

Overview

The TPL8052Q series supports operating with 3 V to 42 V (45-V maximum transient voltage). Operating with as low as 3 V allows the TPL8052Q to continue to work well during cold-crank and start-stop conditions.

The TPL8052Q is a series of 5- μ A ultra-low quiescent low dropout voltage linear regulators with 450-mA maximum output current capability.

With the above features, the TPL8052Q products are the optimal solutions for powering the MCU, CAN/LIN transceivers in the always-on applications, and the battery-connected applications in the automotive systems.

The TPL8052Q series provides an adjustable output voltage option, and the TPL8052Q supports a wide range of output capacitors from 1 μ F to 200 μ F with an ESR range from 0.001 Ω to 5 Ω . Also, the TPL8052Q series integrates over-current protection and over-temperature protection.

Functional Block Diagram




Figure 10. Functional Block Diagram

Feature Description

Enable (EN)

The enable pin (EN) is active high. Connect this pin to the GPIO of an external processor or digital logic control circuit to enable and disable the device. Or connect this pin to the IN pin for self-bias applications.

42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Under-Voltage Lockout (UVLO)

The TPL8052Q series uses an under-voltage lockout circuit to keep the output shut off until the internal circuitry operates properly. Refer to the Electrical Characteristics table for UVLO threshold and hysteresis.

Regulated Output Voltage (OUT)

When the input voltage is higher than $V_{OUT(NOM)} + V_{DO}$, the output pin is the regulated output based on the selected voltage version. When the input voltage falls below $V_{OUT(NOM)} + V_{DO}$, the output pin tracks the input voltage minus the dropout voltage based on the load current.

Adjustable Output Voltage

Use the external resistor divider to select an output voltage between 0.6 V and 21 V. Use the following Equation to calculate the output voltage.

$$V_{OUT} = V_{FB} \times \left(1 + \frac{R1}{R2}\right) \quad (1)$$

Over-Current Protection

The TPL8052Q series integrates an internal current limit that helps to protect the regulator during fault conditions, e.g., the output is shorted to ground, or the output is forced below $V_{OUT(NOM)}$. The output voltage is not regulated when the device is in current limit, and $V_{OUT} = I_{CL} \times R_{LOAD}$.

Over-Temperature Protection

The over-temperature protection starts to work when the junction temperature exceeds the thermal shutdown (T_{SD}) threshold, which turns off the regulator immediately. Until when the device cools down and the junction temperature falls below the thermal shutdown threshold minus thermal shutdown hysteresis, the regulator turns on again. The junction temperature range should be limited according to the Recommended Operating Conditions table, continuously operating above the junction temperature range will reduce the device lifetime.

Application and Implementation

Note

Information in the following application sections is not part of the 3PEAK's component specification and 3PEAK does not warrant its accuracy or completeness. 3PEAK's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

Application Information

The TPL8052Q products are 42-V 5- μ A ultra-low quiescent low dropout voltage linear regulators with 450-mA maximum output current capability. The following application schematic shows a typical usage of the TPL8052Q series.

Typical Application

Figure 11 shows the typical application schematic of the TPL8052Q series.




Figure 11. Typical Application Circuit

Input Capacitor and Output Capacitor

The device requires an input decoupling capacitor with a recommended value above 1 μ F. The voltage rating of the capacitors must be greater than the maximum input voltage.

To ensure loop stability, the TPL8052Q series requires an output capacitor of 1 μ F to 200 μ F with an ESR range from 0.001 Ω to 5 Ω . 3PEAK recommends selecting an X7R type 10- μ F ceramic capacitor with low ESR over temperature.

Both input and output capacitors must be placed as close to the device pins as possible.

Power Dissipation and Thermal Consideration

During normal operation, the LDO junction temperature should meet the requirements in the [Recommended Operating Conditions](#) table. Use the equations below to calculate the power dissipation and estimate the junction temperature.

The power dissipation can be calculated using the [Equation 2](#).

$$P_D = (V_{IN} - V_{OUT}) \times I_{OUT} + V_{IN} \times I_{GND} \quad (2)$$



The junction temperature can be estimated using the [Equation 3](#). θ_{JA} is the junction-to-ambient thermal resistance.

$$T_J = T_A + P_D \times \theta_{JA} \quad (3)$$

**42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout
Linear Regulator****Layout****Layout Guideline**

- Both input and output capacitors must be placed to the device pins as close as possible, and the vias between capacitors and device power pins must be avoided.
- It is recommended to bypass the input pin to ground with a 0.1- μ F bypass capacitor. The loop area formed by the bypass capacitor connection, the IN pin, and the GND pin of the system must be as small as possible.
- It is recommended to use wide and thick copper to minimize $I \times R$ drop and heat dissipation.

Tape and Reel Information




Order Number	Package	D1 (mm)	W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P0 (mm)	W0 (mm)	Pin1 Quadrant
TPL8052ADQ-EV1R-S	EMSOP8	330	17.6	5.3	3.4	1.4	8	12	Q1

42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout Linear Regulator

Package Outline Dimensions

EMSOP8



**42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout
Linear Regulator****Order Information**

Order Number	Operating Temperature Range	Package	Marking Information	MSL	Transport Media, Quantity	Eco Plan
TPL8052ADQ-EV1R-S	-40 to 125°C	EMSOP8	L52AD	MSL3	3,000	Green

Green: 3PEAK defines "Green" to mean RoHS compatible and free of halogen substances.

**42-V/450-mA Wide-Input Ultra-low Quiescent Current Low-Dropout
Linear Regulator****IMPORTANT NOTICE AND DISCLAIMER**

Copyright© 3PEAK 2012-2025. All rights reserved.

Trademarks. Any of the 思瑞浦 or 3PEAK trade names, trademarks, graphic marks, and domain names contained in this document /material are the property of 3PEAK. You may NOT reproduce, modify, publish, transmit or distribute any Trademark without the prior written consent of 3PEAK.

Performance Information. Performance tests or performance range contained in this document/material are either results of design simulation or actual tests conducted under designated testing environment. Any variation in testing environment or simulation environment, including but not limited to testing method, testing process or testing temperature, may affect actual performance of the product.

Disclaimer. 3PEAK provides technical and reliability data (including data sheets), design resources (including reference designs), application or other design recommendations, networking tools, security information and other resources "As Is". 3PEAK makes no warranty as to the absence of defects, and makes no warranties of any kind, express or implied, including without limitation, implied warranties as to merchantability, fitness for a particular purpose or non-infringement of any third-party's intellectual property rights. Unless otherwise specified in writing, products supplied by 3PEAK are not designed to be used in any life-threatening scenarios, including critical medical applications, automotive safety-critical systems, aviation, aerospace, or any situations where failure could result in bodily harm, loss of life, or significant property damage. 3PEAK disclaims all liability for any such unauthorized use.

This page intentionally left blank